

MA610 600A Clamp Meter + NCV



The MA610 is a fully loaded clamp meter with multimeter functions including AC Current, AC/DC Voltage, Resistance, Frequency, and Capacitance. It also has a built-in non-contact voltage (NCV) detector to quickly check circuits and wires for live voltages.



Features

- Pocket-sized meter with 1.2" (30mm) jaw size fits conductors up to 500MCM
- Built-in Non-Contact Voltage (NCV) detector
- MultiMeter functions include Resistance, Capacitance and Frequency
- Relative Mode for Capacitance
- Data Hold freezes reading on display
- Auto Power Off with disable and Low Battery indication
- Large backlit LCD display
- Complete with test leads, three AAA batteries, and pouch

Specifications	Range	Max Resolution	Basic Accuracy
AC Current	600.0A	1mA	±2.0%
DC Voltage	600V	0.1mV	±0.8%
AC Voltage	600V	1mV	±1.2%
Non-Contact Voltage (NCV)	100 to 600V		
Resistance	40MΩ	0.1Ω	
Capacitance	100μF	0.01nF	
Frequency	1MHz	0.01Hz	
Diode/Continuity	Yes		
Dimensions/Weight	9x3x1.6" (228x77x41mm)/ 9.3oz (265g)		

Ordering

MA610 **N** 600A AC Clamp Meter

N Indicates products that are available with optional calibration traceable to NIST. Order with -NIST after part number.



UPC Code: 793950376119